LUXION LX-RM63 remote control for curtain motor

63-channel remote control for easy operation of the LUXION LX-CM01 and LX-CM02 curtain motors.



CODES

Colour	Code
–	LX-RM63

SPECIFICATIONS

Brand	LUXION
Category	Smart home › Electric curtains
Product type	Remote control for curtain motor
Functions	Channel indicator, open, stop, close, memory, left / right channel selection
Number of channels	63 (1 motor per channel)
Operating voltage	3 V – 2 × AAA batteries
RF frequency	868 MHz
Compatibility	LUXION LX-CM01 and LX-CM02 curtain motors (LUXION products only)
Material	Plastic
Protection rating	IP20

DESCRIPTION

The remote control lets you operate your LUXION curtains with ease via the LX-CM01 and LX-CM02 curtain motors.

The product is compatible only with LUXION products and is also included in the complete kits.

Features

Full remote control of your curtains, with a separate channel for each motor.

- Functions: channel indicator, open, stop, close, memory, left / right channel selection
- 63 channels (1 motor per channel)
- Operating frequency 868 MHz
- 3V power supply from 2 AAA batteries
- Compatible with the LUXION LX-CM01 and LX-CM02 curtain motors

Remote control buttons

- Channel indicator
- Open
- Stop
- Close
- Right and left (channel selection)
- Memory button on the back

Motor controls

- Memory button
- LED indicator

Pairing the remote control

Follow the steps below to pair the remote control with the curtain motor.

- 1. Press the motor's memory button for about 3 seconds until the LED lights up, then release it.
- 2. Press the left or right button on the remote control to select the channel.
- 3. Once you have confirmed the channel, press the memory button on the back of the remote control.
- 4. When the motor's LED goes out, the code has been memorised successfully.