LUXION by Case-Smart®

DATASHEET
LX-6.2TRACK

LUXION 6.2 m Wi-Fi electric curtain track kit with remote control

6.2 m smart curtain track kit with motor, remote control and Wi-Fi control from the Smart Life app, no hub required.



CODES

Colour	Code
White	LX-6.2TRACK

SPECIFICATIONS

Brand	LUXION
Category	Smart home › Electric curtains
Connectivity	Wi-Fi
Product type	6.2 m electric curtain track kit
Function	Remote control, mobile app, curtain switch, voice control, scheduling
Operating voltage	100–240 V AC
Frequency	50/60 Hz
Rated current	0.3 A
Power	80 W
Maximum load	50 kg
Torque	2.5 Nm
Insulation class	E
Neutral wire (N)	Required
Protocol	Wi-Fi (no hub)
App	Smart Life
Compatibility	iOS / Android
Motor wiring	485 interface; grey: left direction, red: live (220 V), blue: neutral, green-yellow: earth, black: right direction
Track material	Metal

Profile dimensions	~3 × ~2.5 cm (W × H)
Motor dimensions	72 × 51 × 300 mm
Belt length when cut	2 × track length + 24 cm
Mounting	Wall brackets (single / double) sold separately
Protection rating	IP41
Package contents	Electric motor, metal track, remote control, belt, fittings

DESCRIPTION

The Luxion smart curtain kit includes an electric motor, a 6-metre metal track, a remote control, a belt and fittings. It is controlled from your mobile phone via the Smart Life app.

The product can be controlled from the remote control, from the mobile app or via a wall switch, such as the Luxion curtain switch. No hub required!

- Voice control
- Scheduling
- Remote control

To mount the track on the wall, the brackets are sold separately:

- Single wall bracket
- Double wall bracket

If the track is cut, the belt is cut according to the formula: 2 x track length + 24 cm.

Features

Complete motorised curtain track kit, with metal track and electric motor.

- Metal track 600 cm (+20 cm for the ends), for a wall length of 622 cm
- Maximum load 50 kg
- 80W motor with 2.5Nm torque
- IP41 protection rating

App control

Wi-Fi control from the Smart Life (Tuya) app, no hub required.

- Smart Life app for iOS / Android
- Remote control
- Control from a wall curtain switch
- Voice control, scheduling and remote control

Structure / components

The kit is assembled from the following components, as shown in the installation diagram.

- Motor
- Drive unit
- Belt
- Pulley
- Bracket
- Extension bracket
- Track
- Roller
- Hook
- Runners (gliders)
- Remote control
- Extension hook
- Ceiling bracket
- Single wall bracket
- Double wall bracket
- Stop (end stop)

- Track profile height: ~2.5 cm
- Motor dimensions: 72 x 51 x 300mm

connection cable.

- 1. Grey wire: left direction
- 2. Red wire: live (220V)
- 3. Blue wire: neutral
- 4. Green-yellow wire: earth
- 5. Black wire: right direction
- Belt cutting: 2 x track length + 24 cm