LUXION 7.2 m Wi-Fi electric curtain track kit with remote control

7.2 m electric curtain track kit with motor, remote control and control via Smart Life (Wi-Fi), no hub required.



CODES

Colour	Code
White	LX-7.2TRACK

SPECIFICATIONS

Brand	LUXION
Category	Smart home › Electric curtains
Connectivity	Wi-Fi
Product type	Wi-Fi electric curtain track kit, 7.2 m
Function	Motorised opening / closing of curtains by remote control, app or switch; voice control, schedules
Operating voltage	100–240 V AC
Frequency	50/60 Hz
Rated current	0.3 A
Power	80 W
Maximum load	50 kg
Torque	2.5 Nm
Neutral (N)	Yes (live, neutral, earth, 2 direction wires)
Protocol	Wi-Fi, no hub; 485 interface
Compatibility	Smart Life app (iOS/Android)
Track length	700 cm (+20 cm for the ends); wall length 722 cm
Track profile dimensions	Width ~3 cm, height ~2.5 cm
Motor dimensions	72 × 51 × 300 mm
Belt cutting	2 × track length + 24 cm

Protection rating	IP41
Package contents	Electric motor, metal track, remote control, belt, accessories (wall brackets sold separately)

DESCRIPTION

The Luxion smart curtain kit includes an electric motor, a 7-metre metal track, a remote control, a belt and accessories. It is controlled from your mobile phone via the Smart Life app.

You can operate it with the remote control, from the app on your phone or with a switch, such as the Luxion curtain switch. No hub required!

Functions: voice control, scheduling and remote control.

To fix the track to the wall, the accessories are sold separately:

- Single wall bracket
- Double wall bracket

If the track is cut, the belt is cut according to the formula: 2 x track length + 24 cm.

Features

Complete motorised curtain track kit, with an 80W motor and a metal track that withstands loads of up to 50 kg.

- Track length 700 cm (+20 cm for the ends), wall length 722 cm
- Maximum load 50 kg
- Torque 2.5Nm
- Protection rating IP41
- No hub required

App control

Control via Wi-Fi from the Smart Life app on iOS and Android, as well as with the remote control or a curtain switch.

- Smart Life app (iOS/Android)
- Remote control
- Voice control
- Scheduling
- Remote access control

Structure / components

The kit is assembled from the components shown in the installation drawing, from the motor and drive unit to the track, the belt and the end pulley.

- Motor
- Drive unit
- Belt
- Pulley
- Bracket
- Extension bracket
- Track
- Roller
- Hook
- Gliders
- Remote control
- Extension hook
- Ceiling bracket
- Single wall bracket
- Double wall bracket
- Stop (end stopper)

Dimensions

Track profile and motor dimensions.

- Profile width: approx. 3 cm
- Profile height: approx. 2.5 cm
- Motor dimensions: 72 x 51 x 300mm

core cable.

- 1. Grey wire: left direction
- 2. Red wire: live (220V)
- 3. Blue wire: neutral
- 4. Green-yellow wire: earth
- 5. Black wire: right direction